Raw Frame Subwoofer Transducers

B&C

21SW152
Diameter: 21 inches
Magnet: NdFeB
Weight: 41 pounds
Qts: 0.30
Vas: 200 liters
Re: 3.4 Ohms
Fs: 32 Hz

bcspeakers.com

Ciare

NDC 21-5
Diameter: 21 inches
Magnet: NdFeB
Weight: 27 pounds
Qts: 0.34
Vas: 270.82 liters
Re: 6.22 Ohms
Fs: 32.2 Hz

ciare.com

Eighteen Sound

21NLW9600
Diameter: 21 inches
Magnet: NdFeB
Weight: 31 pounds
Qts: 0.22
Vas: 304 liters
Re: 6 Ohms
Fs: 29 Hz

eighteensound.com

P.Audio

SD21-1800EL
Diameter: 21 inches
Magnet: Ferrite
Weight: 71 pounds
Qts: 0.29
Vas: 259.76 liters
Re: 6 Ohms
Fs: 35 Hz

paudiothailand.com

RCF

LF21N451
Diameter: 21 inches
Magnet: NdFeB
Weight: 24 pounds
Qts: 0.26
Vas: 375 liters
Re: 5.6 Ohms
Fs: 30 Hz

rcf.it

Beyma

18SW1600N
Diameter: 18 inches
Magnet: NdFeB
Weight: 25 pounds
Qts: 0.33
Vas: 205.7 liters
Re: 5.5 Ohms
Fs: 32 Hz

beyma.com

BMS

18N860
Diameter: 18 inches
Magnet: NdFeB
Weight: 23 pounds
Qts: 0.37
Vas: 304 liters
Re: 5.7 Ohms
Fs: 24.85 Hz

bmsspeakers.com

Celestion

CF18VJD
Diameter: 18 inches
Magnet: Ferrite
Weight: 51 pounds
Qts: 0.305
Vas: 164 liters
Re: 5.51 Ohms
Fs: 33.1 Hz

celestion.com

Electro-Voice

DVX-3150
Diameter: 15 inches
Magnet: Ferrite
Weight: 18 pounds
Qts: 0.35
Vas: 132 liters
Re: 5.26 Ohms
Fs: 46.8 Hz

electrovoice.com

Eminence

Definimax 4018LF
Diameter: 18 inches
Magnet: Ferrite
Weight: 23 pounds
Qts: 0.35
Vas: 237.9 liters
Re: 6.19 Ohms
Fs: 32 Hz

eminence.com

FaitalPRO

18XL1600
Diameter: 18 inches
Magnet: NdFeB
Weight: 27 pounds
Qts: 0.36
Vas: 195.5 liters
Re: 5.4 Ohms
Fs: 32 Hz

faitalpro.com

Fane

Prime 18X5
Diameter: 18 inches
Magnet: Ferrite
Weight: 34 pounds
Qts: 0.385
Vas: 257 liters
Re: 5.2 Ohms
Fs: 33 Hz

fane-international.com

JBL

2269H
Diameter: 18 inches
Magnet: NdFeB
Weight: 21 pounds
Qts: 0.36
Vas: 237 liters
Re: 5.3 Ohms
Fs: 28 Hz

jblpro.com

McCauley

D174
Diameter: 18 inches
Magnet: NdFeB
Weight: 23 pounds
Qts: 0.263
Vas: 289.4 liters
Re: 4.92 Ohms
Fs: 29.4 Hz

mccauleysound.com

Peavey

Lo Max 18
Diameter: 18 inches
Magnet: Ferrite
Weight: 34 pounds
Qts: 0.386
Vas: 294.4 liters
Re: 5.4 Ohms
Fs: 31.5 Hz

peavey.com

Selenium

18SW51000
Diameter: 18 inches
Magnet: Ferrite
Weight: 31 pounds
Qts: 0.48
Vas: 212 liters
Re: 5.6 Ohms
Fs: 39 Hz

selenium.com.br

WorxAudio

TL180155
Diameter: 18 inches
Magnet: NdFeB
Weight: 52 pounds
Qts: 0.3882
Vas: 259.3 liters
Re: 3.75 Ohms
Fs: 27.59 Hz

worxaudio.com

Radian

2210
Diameter: 10 inches
Magnet: Ferrite
Weight: 12 pounds
Qts: 0.426
Vas: 23 liters
Re: 5.4 Ohms
Fs: 64 Hz

radianaudio.com